



Digital AC Ammeter, DAA-1



Digital AC Voltmeter, DAV-1



Digital DC Ammeter, DDA-1



Digital DC Voltmeter, DDV-1

Features:

- Four ranges
- 2000 counts display
- Simple and extremely safe to use
- Safety sockets and dual insulation

Technical Data	DAA-1	DAV-1	DDA-1	DDV-1
Type	AC current meter	AC voltage meter	DC current meter	DC voltage meter
Range/Resolution	2mA/0.001mA 20mA/0.01mA 200mA/0.1mA 5A/0.01A	2V/0.001V 20V/0.01V 200V/0.1V 600V/1V	2mA/0.001mA 20mA/0.01mA 200mA/0.1mA 5A/0.01A	200mV/0.1mV 2V/0.001V 20V/0.01V 200V/0.1V
Accuracy	±(1.2%+2 digits)/ (2mA/20mA/200mA) ±(1.5%+3 digits)/ (5A)	±(1%+2 digits)	±(1%+1 digits)/ (2mA/20mA/200mA) ±(1.5%+2 digits)/ (5A)	±(0.5%+1 digits)/ (200mV) ±(0.8%+1 digits)/ (2V/20V/200V)
Fuse	5A(5A) 500mA(2mA/ 20mA/200mA)	N/A	5A(5A) 500mA(2mA/ 20mA/200mA)	N/A
Dimensions	190×140×80 mm			
Weight	150g			